

## **ELEKTRIK MOTOR**































#### **MOUNTINGS AND POSITIONS**





- Frame B3
- 2. Frame B5
- 3. Wound Stator
- Rotor with shaft 4.
- 5. Front shield
- 6. Bearings
- 7. Key
- 8. Back shield
- 9. Name plate
- 10. Compensation ring
- 11. Bolts and nuts
- 12. Cooling fan
- Fan clamping bushing 13.
- Rubber seal ring 14.
- 15. Fan cover
- Self-threading screws for fan cover fixing
- 17. Terminal board complete with components
- 18. Terminal seal IP55
- 19. Screws for terminal box fixing IP56
- 20. Cable press
- 21. Terminal box IP65(base)
- 22. Terminal box IP65(cover)
- Run capacitor
- Mounting studs screws
- 25. Start capacitor
- 26. Flange B5
- 27. Flange B14
- 28. Screws for terminal

## **OUNTINGS AND POSITIONS**

Mountings and positions for standard motors, according to IEC 60034-7, are dened by the codes mentioned in following table

		STANDARD	The same of the sa	FRAME SIZES
No.	CEI 2-14	Code I	0034-7 Code II	56-132
<b>1</b>	В3	IM B3	IM 1001	Standard
	B3/B5	IM B35	IM 2001	Standard
1	B5	IM B5	IM 3001	Standard
	B14	IM B14	IM 4001	Standard
-6	B8	IM B8	IM 1071	Upon request
	В6	IM B6	IM 1051	Upon request
<b>%</b> -	В7	IM B7	IM 1061	Upon request

		STANDARD	S	FRAME SIZES
	CEI 2-14	IEC 6	0034-7	56-132
		Code I	Code II	
車	V1	IM V1	IM 3011	Standard
	V3	IM V3	IM 3031	Upon request
	V5	IM V5	IM 1011	Upon request
	V6	IM V6	IM 1031	Upon request
	V1/V5	IMV15	IM 2011	Upon request

#### **Aluminum Housing Electric Motors Bearings & Oilseals**

Frame	Bea	rings	Oil	seals	Thread of
	Drive end	Non-drive end	Drive end	Non-drive end	Cable Gland
56	6201	6201	12x22x5	12x22x5	M16
53	6201	6201	12x24x7	12x24x7	M16
71	6202	6202	15x25x7	15x25x7	M20
30	6204	6204	20x34x7	20x34x7	M20
905	6205	6205(6204)	25x37x7	25x37x7(20x34x7)	M25
OL	6205	6205(6204)	25x37x7	25x37x7(20x34x7)	M25
100L	6206	6206	30x42x7	30x42x7	M25
112M	6306	6206	30x42x7	30x42x7	M25
1325	6308	6208	40x58x8	40x58x8	M32
32M	6308	6208	40x58x8	40x58x8	M32
60M	6309	6309	45x65x8	45x65x8	M32
160L	6309	6309	45x65x8	45x65x8	M32

Other standard is also available as per request. The gures in bracket " () " is for the single phase motors.



# TA

## SERIES THREE-PHASE ASYNCRONOUS MOTORS

## **ALUMINIUM HOUSING**











**TA** series aluminum housing three-phase asynchronous motors, with latest design in entirety, are made of selected quality materials and conform to the IEC standard.

**TA** motors have good performance, safety and reliable operation, nice appearance, and can be maintained very conveniently, while with low noises, little vibration and at the same time light weight and simple construction. These series motors can be used for general drive.



#### ECHNICAL DATA 2P @ 50HZ

Model	Power (kW)		Current (A	A)	(	Current (A	)		Current (A	4)	Speed (r/min)	Eff. (%)	Power Factor	Tstart/Tn (Times)	Tmax/Tn (Times)	Tmax/Tn (Times)	Is/In (Times)	Noise dB(A)	W.t
		220V	380V	660V	230V	400V	690V	240V	415V	720V		No. 100.1		7.00-11865.0	N-mosels.	UNIVERSAL.	Montecon		0.00
TA - 561- 2	0.09	0.64	0.37	0.21	0.61	0.35	0.20	0.58	0.34	0.19	2670	57	0.65	2.2	2.4	1.6	6	58	2.8
TA - 562- 2	0.12	0.74	0.43	0.25	0.70	0.40	0.23	0.67	0.39	0.22	2730	62	0.69	2.2	2.4	1.6	6	58	3.2
TA - 563- 2	0.18	1.00	0.58	0.34	0.96	0.56	0.32	0.93	0.54	0.31	2750	65	0.72	2.2	2.4	1.6	6	59	3.
TA - 631- 2	0.18	1.00	0.58	0.33	0.95	0.55	0.32	0.92	0.53	0.31	2710	63	0.75	2.2	2.4	1.6	6	61	4
TA - 632- 2	0.25	1.29	0.75	0.43	1.23	0.71	0.41	1.19	0.69	0.40	2710	65	0.78	2.2	2.4	1.6	6	61	4.
TA - 633- 2	0.37	1.92	1.11	0.64	1.82	1.05	0.61	1.76	1.02	0.59	2710	65	0.78	2.2	2.4	1.6	6	62	4.
TA - 711- 2	0.37	1.76	1.02	0.59	1.67	0.97	0.56	1.61	0.93	0.54	2730	70	0.79	2.2	2.4	1.6	6	64	5
TA - 712- 2	0.55	2.57	1.49	0.86	2.45	1.42	0.82	2.36	1.36	0.79	2760	71	0.79	2.2	2.4	1.6	6	64	6
TA - 713- 2	0.75	3.33	1.93	1.11	3.18	1.83	1.06	3.06	1.77	1.02	2730	72	0.82	2.2	2.4	1.5	6	65	
TA - 801- 2	0.75	3.21	1.86	1.07	3.06	1.77	1.02	2.94	1.70	0.98	2770	73	0.84	2.2	2.4	1.5	6	67	9
TA - 802- 2	1.1	4.56	2.64	1.52	4.35	2.51	1.45	4.18	2.42	1.39	2770	76.2	0.83	2.2	2.4	1.5	6	67	10
TA - 803-2	1.5	6.04	3.50	2.01	5.87	3.32	1.92	5.54	3.20	1.85	2800	78.5	0.83	2.2	2.4	1.5	6	70	11
TA - 905- 2	1.5	5.97	3.46	1.99	5.76	3.28	1.90	5.47	3.16	1.82	2840	78.5	0.84	2.2	2.4	15	6	72	1
TA - 90L1- 2	2.2	8.39	4.85	2.80	8.0	4.61	2.66	7.69	4.45	2.56	2840	81	0.85	2.2	2.4	1.4	6	72	1
TA - 90L2- 2	3	11.08	6.42	3.69	10.56	6.10	3.52	10.16	5.88	3.39	2840	82.6	0.86	2.2	2.4	1.4	6	74	18
TA - 100L1- 2	3	10.96	6.34	3.65	10.44	6.03	3.48	10.04	5.81	3.35	2840	82.6	0.87	2.2	2.3	1.4	7	76	22
TA - 100L2- 2	4	14.33	8.30	4.78	13.65	7.88	4.55	13.14	7.60	4.38	2850	84.2	0.87	2.2	2.3	1.4	7.5	77	25
TA - 112M- 2	4	14.33	8.30	4.78	13.65	7.88	4.55	13.14	7.60	4.38	2880	84.2	0.87	2.2	2.3	1.4	7.5	77	26
TA - 112L- 2	5.5	19.14	11.08	6.38	18.23	10.53	6.08	17.54	10.15	5.85	2880	85.7	0.88	2.2	2.3	1.2	7.5	78	30
TA - 132S1- 2	5.5	19.14	11.08	6.38	18.23	10.53	6.08	17.54	10.15	5.85	2900	85.7	0.88	2	2.2	1.2	7.5	80	38
TA - 132S2- 2	7.5	25.71	14.88	8.57	24.49	14.14	8.16	23.57	13.63	7.86	2920	87	0.88	2	2.2	1.2	7.5	80	42
TA - 132M1- 2	9.2	30.86	17.85	10.28	29.87	17.25	9.96	28.26	16.34	9.42	2930	88	0.89	2	2.2	1.2	7.5	81	51
TA - 132M2- 2	11	36.28	21.01	12.09	34.57	19.96	11.52	33.26	19.23	11.09	2930	88.4	0.9	2	2.2	1.2	7,5	83	58
TA - 160M1- 2	11	36.28	21.01	12.09	34.57	19.96	11.52	33.26	19.23	11.09	2940	88.4	0.9	2	2.2	1.2	7.5	86	7
TA - 160M2- 2	15	48.39	28.01	16.13	46.09	26.61	15.36	44.35	25.62	14.78	2940	89.4	0.91	2	2.2	1.2	7.5	86	8
TA - 160L- 2	18.5	59.28	34.32	19.76	56.47	32.6	18.82	54.34	31.43	18.11	2940	90	0.91	2	2.2	1.1	7.5	86	9






## F ECHNICAL DATA 4P, 6P, 8P @ 50HZ

Model	Power	C	urrent (A	A)		Current (A	).		Current (A	)	Speed	Eff.	Power		Tmax/Tn	TO SHARE THE PARTY OF THE	Is/In	Noise	W.t.
Model	(kW)	220V	380V	660V	230V	400V	690V	240V	415V	720V	(r/min)	(%)	Factor	(Times)	(Times)	(Times)	(Times)	dB(A)	(Kg)
TA - 561- 4	0.06	0.55	0.32	0.18	0.52	0.30	0.17	0.50	0.29	0.17	1320	48.5	0.59	2.3	2.4	1.7	6	50	3
TA - 562- 4	0.09	0.77	0.45	0.26	0.74	0.43	0.25	0.71	0.41	0.24	1320	50	0.61	2.3	2.4	1.7	6	50	3.3
TA - 563- 4	0.12	0.96	0.56	0.32	0.92	0.53	0.31	0.88	-0.51	0.29	1320	52	0.63	2.2	2.4	1.7	6	51	3.5
TA - 631- 4	0.12	0.86	0.50	0.29	0.82	0.47	0.27	0.79	0.46	0.26	1350	57	0.64	2.2	2.4	1.7	6	52	3.9
TA - 632- 4	0.18	1.23	0.71	0.41	1.17	0.68	0.39	1.13	0.65	0.38	1350	59	0.65	2.2	2.4	1.7	6	52	4.3
TA - 633- 4	0.25	1.66	0.96	0.55	1.58	0.91	0.53	1.52	0.88	0.51	1350	60	0.66	2.2	2.4	1.7	6	54	4.8
TA - 711- 4	0.25	152	0.88	0.51	1.45	0.84	0.48	1.39	0.81	0.46	1350	60	0.72	2.2	2.4	1.7	6	55	5.4
TA - 712- 4	0.37	2.02	1.17	0.67	1.92	1.11	0.64	1.85	1.07	0.62	1370	65	0.74	2.2	2.4	1.7	6	55	6.2
TA - 713- 4	0.55	2.92	1.69	0.97	2.78	1.60	0.93	2.67	1.55	0.89	1380	66	0.75	2.2	2.4	1.7	6	57	7.3
TA - 801- 4	0.55	2.87	1.66	0.96	2.74	1.58	0.91	2.63	1.52	0.88	1370	67	0.75	2.2	2.4	1.7	6	58	9
TA - 802- 4	0.75	3.50	2.03	1.17	3.34	1.93	1.11	3.21	1.86	1.07	1380	72	0.78	2.2	2.4	1.5	6	58	10
TA - 803- 4	1.1	4.86	2.81	1.62	4.63	2.67	1.54	4.45	2.57	1.48	1390	76.2	0.78	2.2	2.4	1.5	6	60	12.
TA - 90S- 4	1.1	4.80	2.78	1.60	4.57	2.64	1.52	4.40	2.54	1.47	1400	76.2	0.79	2.2	2.4	1.5	6	61	12.
TA - 90L- 4	1.5	6.27	3.63	2.09	5.97	3,45	1.99	5.75	3.32	1.92	1400	78.5	0.8	2.2	2.4	1.5	6	61	14.
TA - 90L2- 4	2.2	8.91	5.16	2.97	8.45	4.90	2.83	8.17	4.72	2.72	1400	81	0.8	2.2	2.4	1.	7	63	18.
TA - 100L1- 4	2.2	8.80	5.09	2.93	8.38	4.84	2.79	8.07	4.66	2.69	1420	81	0.81	2.2	2.3	1.5	7	64	21
TA - 100L2- 4	3	11.77	6.81	3.92	11.21	6.47	3.74	10.79	6.24	3.60	1420	82.6	0.81	2.2	2.3	1.5	7	64	24.
TA - 100L3- 4	4	15.20	8.80	5.07	14.18	8.36	4.83	13.94	8.06	4.65	1430	84.2	0.82	2.2	2.2	1.5	7	65	29
TA - 112M- 4	4	15.02	8.70	5.01	14.31	8.26	4.77	13.77	7.96	4.59	1430	84.2	0.83	2.2	2.2	1.5	7	65	30.
TA - 112L- 4	5.5	20.29	11.75	6.76	19.33	11.16	6.44	18.60	10.76	6.20	1440	85.7	0.83	2.2	2.2	1.4	7	68	34.
TA - 132S- 4	5.5	20.05	11.61	6.68	19.1	11.03	6.37	18.38	10.63	6.13	1450	85.7	0.84	2.2	2.2	1.4	7	71	40.
TA - 132M- 4	7.5	26.62	15.41	8.87	25.35	14.64	8.45	24.40	14.11	8.13	1450	87	0.85	2.2	2.2	1.4	7	71	49.
TA - 132L1- 4	9.2	32.46	18.79	10.82	30.92	17.85	10.31	29.76	17.21	9.92	1460	87.5	0.85	2.2	2.2	1.4	7.5	74	56.
TA - 132L2- 4	10	35.08	20.31	11.69	33.42	19.3	11.14	32.16	18.60	10.72	1460	88	0.85	2.2	2.2	1.4	7.5	74	58.
TA - 132L3- 4	11	37.97	21.98	12.66	36.17	20.88	12.06	34.81	20.13	11.60	1460	88.4	0.86	2.2	2.2	1.4	7.5	74	64
TA - 160M- 4	11	37.54	21.73	12.51	35.76	20.64	11.92	34.41	19.90	11.47	1460	88.4	0.87	2.2	2.2	1.4	7	75	78
TA - 160L- 4	15	51.18	29.63	17.06	48.76	28.15	16.25	46.92	27.13	15.64	1460	88.4	0.87	2.2	2.2	1.4	7.5	75	98
TA - 631- 6	0.09	0.92	0.53	0.31	0.88	0.51	0.29	0.85	0.49	0.28	840	42	0.61	2	2	1.5	3.5	50	4.2
TA - 632- 6	0.12	1.129	0.65	0.38	1.08	0.62	0.36	1.03	0.60	0.34	850	45	0.62	2	2	1.5	3.5	50	4.8
TA - 711- 6	0.18	1.28	0.74	0.43	1.22	0.70	0.41	1.17	0.68	0.39	880	56	0.66	1.6	1.7	1.5	4	52	6
TA - 712- 6 TA - 713- 6	0.25	1.6	1.34	0.53	1.51	0.87	0.50	1.46	1.22	0.49	900	59	0.7	2.1	2.2	1.5	4	52 54	7.2
TA - 801- 6	0.37	2.24	1.30	0.75	2.13	1.23	0.73	2.05	1.19	0.70	900	62	0.09	1.9	1.9	1.5	4	56	8.2
TA - 802- 6	0.55	2.99	1.73	1.00	2.85	1.65	0.95	2.74	1.59	0.00	900	67	0.72	2	2.3	1.5	4	56	9.9
TA - 803- 6	0.75	4.02	2.33	1.34	3.83	2.21	1.28	3.69	2.13	1.23	900	68	0.72	2	2.3	1.5	4	58	11.
TA - 90S- 6	0.75	3.96	2.29	1.32	3.77	2.18	1.26	3.63	2.10	1.21	920	69	0.72	2.2	2.2	1.5	5.5	59	11.
TA - 90L- 6	1.1	5.49	3.18	1.83	5.23	3.02	1.74	5.03	2.91	1.68	925	72	0.73	2.2	2.2	1.3	5.5	59	15.
TA - 100L- 6	1.5	7.00	4.05	2.33	6.67	3.85	2.22	6.42	3.71	2.14	945	74	0.76	2.2	2.2	1.3	6	61	19.
TA - 112M- 6	2.2	9.74	5.64	3.25	9.28	5.36	3.09	8.93	5.16	2.98	955	78	0.76	2.2	2.2	1.3	6	64	25.
TA - 132S- 6	3	13.11	7.59	4.37	12.49	7.21	4.16	12.02	6.95	4.01	960	79	0.76	2	2	1.3	6.5	64	36.
TA - 132M1- 6	4	17.16	9.93	5.72	16.35	9.44	5.45	15.73	9.10	5.24	960	80.5	0.76	2	2	1.3	6.5	68	45
TA - 132M2- 6	5.5	22.58	13.08	1000	21.51	12.42	7.17	20.70	11.97	6.90	960	83	0.77	2	2	1.3	6.5	68	55.
TA - 132L- 6	7.5	30.07	17.41	10.02	10.00	16.54	9.55	27.57	15.94	9.19	960	85	0.77	2	2	1.3	6.5	68	60
TA - 160M- 6	7.5	28.61	16.56	9.54	27.25	15.73	9.08	26.22	15.17	8.74	960	86	0.8	2	2.2	1.3	6.5	68	72
TA - 160L- 6	11	41.76	24.18	13.92		22.97	13.26	38.28	22.14	12.76	960	87.5	0.79	2	2.2	1.3	6.5	73	92
TA - 711- 8	0.09	0.88	0.51	0.29	0.84	0.48	0.28	0.81	0.47	0.27	680	48	0.56	1.5	1.7	1.3	3	50	6
TA - 712- 8	0.12	1.05	0.61	0.35	1.00	0.58	0.33	0.96	0.55	0.32	690	51	0.59	1.6	1.7	1.3	2.7	50	6.8
TA - 801- 8	0.18	1.52	0.88	0.51	1.45	0.84	0.48	1.39	0.80	0.46	680	51	0.61	1.5	1.7	1.3	2.8	52	9.9
TA - 802- 8	0.25	1.92	1.11	0.64	1.83	1.06	0.61	1.76	1.02	0.59	680	56	0.61	1.6	2	1.3	2.7	52	10.
TA - 803- 8	0.37	2.45	1.42	0.82	2.33	1.35	0.78	2.24	1.30	0.75	680	63	0.63	1.6	1.8	1.3	2.8	56	14.
TA - 90S- 8	0.55	3.36	1.95	1.12	3.21	1.85	1.07	3.08	1.78	1.03	680	66	0.65	1.6	1.8	1.3	3	56	17
TA - 100L1- 8	0.75	4.45	2.58	1.48	4.24	2.45	1.41	4.08	2.36	1.36	710	66	0.67	1.7	2.1	1.3	3.5	59	17.
TA - 100L2- 8	1.1	5.81	3.36	1.94	5.54	3.20	1.85	5.33	3.08	1.78	710	72	0.69	1.7	2.1	1.2	3.5	59	19
TA - 112M- 8	1.5	7.82	4.53	2,61	7.45	4.30	2.48	7.17	4.15	2.39	710	74	0.68	1.8	2.1	1.2	4.2	61	25.
TA - 132S- 8	2.2	10.84	6.28	3.61	10.33	5.96	3.44	9.94	5.75	3.31	720	75	0.71	2	2	1.2	5.5	64	35
TA - 132M- 8	3	14.01	8.11	4.67	13.34	7.70	4.45	12.84	7.43	4.28	720	77	0.73	2	2	1.2	5.5	64	45
TA - 160M1- 8	4	17.97	10.41	5.99	17.12	9.89	5.71	16.48	9.53	5.49	730	80	0.73	1.9	2.1	1.2	6	68	60
TA - 160M2- 8	5.5	23.36	13.52	7.79	22.25	12.85	7.42	21.41	12.38	7.14	720	83.5	0.74	2	2.2	1.2	6	68	72
TA - 160L- 8	7.5	30.87	17.87	10.29	29.41	17.0	9.8	28.30	16.37	9.43	720	85	0.75	1.9	2.2	1.2	6	68	92



## DIMENSION



IMB3

IMB5

IMB14



## **VERALL & INSTALLATION DIMENSIONS**

#### **B3 Overall & Installation Dimension**

FRAME	Н	А	В	С	D	E	F	G	К	M	AD	AC	L	Lcc	Lca	Lam	KK	TBS	TBW	твн	SS	XX	ZZ	СС	Υ
56	56	90	71	36	Ф9	20	3	7.2	5.8X8.8	110	156/151	Ф120	195				1-M16X1.5	14/21	88/73	88/73	МЗ	8	12	2.5	0.5
63	63	100	80	40	Ф11	23	4	8.5	7X10	120	173/165	Ф130	215	232	265	283	1-M16X1.5	14/21	94/80	94/80	M4	10	15	3.3	0.8
71	71	112	90	45	Ф14	30	5	11	7X10	132	188/180	Φ145	240(254)	252(267)	307	345	1-M20X1.5	20/27	94/80	94/80	M5	12	18	4.2	0.8
80	80	125	100	50	Ф19	40	6	15.5	10X13	160	217	Ф165	290	300	353	390	1-M20X1.5	27	105	105	M6	16	22	5	1
90S	90	140	100	56	Ф24	50	8	20	10X13	175	235	Ф185	310	320	367	448	1-M20X1.5	30	105	105	M8	20	25	6.8	1
90L1/L2	90	140	125	56	Ф24	50	8	20	10X13	175	235	Ф185	335/365	345/375	392	463	1-M20X1,5	30	105	105	M8	20	25	6.8	1
100	100	160	140	63	Ф28	60	8	24	12X16	196	252	Ф205	368(386)	392(410)	474	445	1-M20X1.5	26	105	105	M10	22	28	8.5	1.5
112	112	190	140	70	Ф28	60	8	24	12X16	220	292	Ф230	395	410	483	455	2-M25X1.5	32	112	119	M10	22	28	8.5	1.5
1328	132	216	140	89	Ф38	80	10	33	12X16	252	325	Ф270	436	468	553	636	2-M2SX1.5	38	112	119	M12	28	34	10.2	1.5
132M/L	132	216	178	89	Ф38	80	10	33	12X16	252	325	Ф270	474/500	484/510	564/590	648/674	2-M25X1.5	38	112	119	M12	28	34	102	1.5
160M/L	160	254	210/254	108	Ф42	110	12	37	15X19	290	390	Ф320	640	652	705	795	2-M32X1.5	64	143	146	M16	35	42	142	2

#### **B5 Overall & Installation Dimension**

FRAME			B5						B5R				D	E	F	G	кк	AC	HD	L	Loc	LccL	LCA	TBS	TBW	твн	SS	××	zz	CC	Y
	М	N	р	Ť	s	R	М	N	Р	Ŧ	s	R																			
56	Ф100	Ф80	Ф120	3.0	Ф7	0							Ф9	20	3	72	1-M16X1.5	Ф120	100/95	195				14/21	88/73	88/73	M3	8	12	2,5	0.5
63	Ф115	Ф95	Ф140	3.0	Ф10	0							Ф11	23	4	8.5	1-M16X1.5	Ф130	110/102	215	232	265	283	14/21	94/80	94/80	M4	10	15	3.3	0.8
71	Ф130	Ф110	Ф160	3.5	Ф10	0	Ф115	Ф95	Ф140	3.0	Ф10	0	Ф14	30	5	.11	1-M20X1.5	Ф145	117/109	240(254)	252(267)	307	345	20/27	94/80	94/80	M5	12	18	42	0.8
80	Ф165	Ф130	Ф200	3.5	Ф12	0	Ф130	Ф110	Ф160	3.5	Ф10	0	Ф19	40	6	15.5	1-M20X1.5	Ф165	137	290	300	353	390	27	105	105	M6	16	22	5	7
90S	Ф165	Ф130	Ф200	3.5	Ф12	0	Ф130	Ф110	Ф160	3.5	Ф12	0	Ф24	50	8	20	1-M20X1.5	Ф185	145	310	320	367	448	30	105	105	M8	20	25	6.8	1
90L1/L2	Ф165	Ф130	Ф200	3.5	Ф12	0	Ф130	Ф110	Ф160	3.5	Ф12	0	Ф24	50	8	20	1-M20X1.5	Ф185	145	335/365	345/375	392	463	30	105	105	M8	20	25	6,8	1
100	Ф215	Ф180	Ф250	4.0	Ф15	0	Ф165	Ф130	Ф200	3.5	Ф12	0	Ф28	60	8	24	1-M20X1.5	Ф205	152	368(386)	392(410)	474	445	26	105	105	M10	22	28	8.5	1.5
112	Ф215	Ф180	Ф250	4.0	Ф15	0	Ф165	Ф130	Ф200	3.5	Ф12	0	Ф28	60	8	24	2-M25X1.5	Ф230	180	395	410	483	455	32	112	119	M10	22	28	8.5	1.5
1325	Ф265	Ф230.	Ф300	4.0	Ф15	0	Ф215	Ф180	Ф250	4.0	Ф15	0	Ф38	80	10	33	2-M25X1.5	Ф270	193	436	468	553	636	38	112	119	M12	28	34	10.2	15
132M/L	Ф265	Ф230	Ф300	4.0	Ф15	0	Ф215	Ф180	Ф250	4.0	Ф15	0	Ф38	80	10	33	2-M25X1.5	Ф270	193	474/500	484/510	564/590	648/674	38	112	119	M12	28	34	10.2	1.5
160M/L	Ф300	Ф250	Ф350	5.0	Ф19	0							Ф42	110	12	37	2-M32X1.5	Ф320	230	640	652	705	795	64	143	146	M16	35	42	14.2	2

#### **B14 Overall & Installation Dimension**


FRAME			B14						B14B	į.			D	E	F	G	KK	AC	HD	L	Lcc	LccL	LCA	TBS	TBW	TBH	SS	XX	ZZ	CC	Y
	N	M	P	Т	s	R	N	M	Р	Ť	S	R																			
56	Ф50	Ф65	Ф80	2.5	M5	0						1	Ф9	20	3	7.2	1-M16X1.5	Ф120	100/95	195				14/21	88/73	88/73	МЗ	8	12	2.5	0.5
63	Ф60	Ф75	Ф90	2.5	M5	0	Ф80	Ф100	Ф120	3.0	M6	0 4	D11	23	4	8.5	1-M16X1.5	Ф130	110/102	215	232	265	283	14/21	94/80	94/80	M4	10	15	3.3	8.0
71	Φ70	Φ85	Ф105	2.5	M6	0	Ф95	Ф115	Ф140	3.0	M8	0 0	D14	30	5	-11	1-M20X1.5	Ф145	117/109	240(254)	252(267)	307	345	20/27	94/80	94/80	M5	12	18	4.2	8.0
80	Ф80	Ф100	Ф120	3.0	M6	0	Ф110	Ф130	Ф160	3.5	M8	0 0	D19	40	6	15.5	1-M20X1.5	Ф165	137	290	300	353	390	27	105	105	M6	16	22	5	1
90S	Ф95	Ф115	Ф140	3.0	M8	0	Ф110	Ф130	Ф160	3.5	M8	0 4	Þ24	50	8	20	1-M20X1.5	Ф185	145	310	320	367	448	30	105	105	M8	20	25	6.8	1
90L1/L2		Ф115	Ф140	3.0	M8	0	Ф110	Ф130	Ф160	3.5	M8	0	Þ24	50	8	20	1-M20X1.5	Ф185	145	335/365	345/375	392	463	30	105	105	M8	20	25	6.8	1
100	Ф110	Ф130	Ф160	3.5	M8	0	Ф130	Ф165	Ф200	3.5	M10	0 4	Þ28	60	8	24	1-M25X1.5	Ф205	152	368(386)	392(410)	474	445	26	105	105	M10	22	28	8.5	1.5
112	Ф110	Ф130	Ф160	3.5	М8	0	Ф130	Ф165	Ф200	3.5	M10	0 4	Þ28	60	8	24	2-M25X1.5	Ф230	180	395	410	483	455	32	112	119	M10	22	28	8.5	1.5
132S	Ф130	Ф165	Ф200	3.5	M10	0	Ф180	Ф215	Ф250	4.0	M12	0	Þ38	80	10	33	2-M25X1.5	Ф270	193	436	468	553	636	38	112	119	M12	28	34	10.2	1.5
132M/L	Ф130	Ф165	Ф200	3.5	M10	0	Ф180	Ф215	Ф250	4.0	M12	0 4	Þ38	80	10	33	2-M32X1.5	Ф270	193	475/500	484/510	564/590	648/674	38	112	119	M12	28	34	10.2	1.5


: For Brake Motors : This frame size has two housing size the rated output is for normal ( refer to the figures in the bracket " ( ) " )




## **DIMENSION**









IMB35

## IMB34 •

#### **B35 Overall & Installation Dimension**

FRAME	н				B35					B35R				A	В	C	D	É	F
		N	M	Р	T	R	S	M	N	Р	T	R	S						
56	56	Ф98	Ф80	Ф120	3.0	0	Ф7							90	71	36	Ф9	20	3
63	63	Ф115	Ф95	Ф140	3.0	0	Ф10	THE R						100	80	40	Ф11	23	4
71 **	71	Ф130	Ф110	Ф160	3.5	0	Ф10	Ф115	Ф95	Ф140	3.0	0	Ф10	112	90	45	Ф14	30	5
80	80	Ф165	Ф130	Ф200	3.5	0	Ф12	Ф130	Ф110	Ф160	3.5	0	Ф10	125	100	50	Ф19	40	6
90S	90	Ф165	Ф130	Ф200	3.5	0	Ф12	Ф130	Ф110	Ф160	3.5	0	Ф12	140	100	56	Ф24	50	8
90L1/L2	90	Ф165	Ф130	Ф200	3.5	0	Ф12	Ф130	Ф110	Ф160	3.5	0	Ф12	140	125	56	Ф24	50	8
100 **	100	Ф215	Ф180	Ф250	4.0	0	Ф15	Ф165	Ф130	Ф200	3.5	0	Ф12	160	140	63	Ф28	60	8
112	112	Ф215	Ф180	Ф250	4.0	0	Ф15	Ф165	Ф130	Ф200	3.5	0	Ф12	190	140	70	Ф28	60	8
132S	132	Ф265	Ф230	Ф300	4.0	0	Ф15	Ф215	Ф180	Ф250	4.0	0	Ф15	216	140	89	Ф38	80	10
132M/L	132	Ф265	Ф230	Ф300	4.0	0	Ф15	Ф215	Ф180	Ф250	4.0	0	Ф15	216	178	89	Ф38	80	10
160M/L	160	Ф300	Ф250	Ф350	5.0	0	Ф19							254	210/254	108	Ф42	110	12

FRAME	G	К	кк	М	AD	AC	L	Lcc *	LcCL*	LcA*	TBS	TBW	твн	SS	xx	ZZ	CC	Y
56	72	5.8x5.8	1-M16X1.5	110	156/151	Ф120	195				14/21	88/73	88/73	M3	8	12	2.5	0.5
63	8.5	7x10	1-M16X1.5	120	173/165	Ф130	215	232	265	283	14/21	94/80	94/80	M4	10	15	3.3	0.8
71 **	11	7x10	1-M20X1.5	132	188/180	Ф145	240(254)	252(267)	307	345	20/27	94/80	94/80	M5	12	18	42	0.8
80	15.5	10x13	1-M20X1.5	160	217	Ф165	290	300	353	390	27	105	105	M6	16	22	5	-1
908	20	10x13	1-M20X1.5	175	235	Ф185	310	320	367	448	30	105	105	M8	20	25	6.8	1
90L1/L2	20	10x13	1-M20X1.5	175	235	Ф185	335/365	345/375	392	463	30	105	105	M8	20	25	6.8	1
100 **	24	10x13	1-M20X1.5	196	252	Ф205	368(386)	392(410)	474	445	26	105	105	M10	22	28	8.5	1.5
112	24	12x16	2-M25X1.5	220	292	Ф230	395	410	483	455	32	112	119	M10	22	28	8.5	1.5
1325	33	12x16	2-M25X1.5	252	325	Ф270	436	468	553	636	38	112	119	M12	28	34	102	1.5
132M/L	33	12x16	2-M25X1.5	252	325	Ф270	474/500	484/510	564/590	648/674	38	112	119	M12	28	34	102	1.5
160M/L	37	15x19	2-M32X1.5	290	390	Ф320	640	652	705	795	64	143	146	M16	35	42	142	- 2

#### **B34 Overall & Installation Dimension**

FRAME	Н	A	В	C	D	E	F	G	K	KK			В	34				
											M	N	P	T	R	S	M	N.
56	56	90	71	36	Ф9	20	3	72	5.8x5.8	1-M16X1.5	Φ65	Ф50	Ф80	2.5	0	M5		
63	63	100	80	40	Ф11	23	4	8.5	7x10	1-M16X1.5	Φ75	Ф60	Ф90	2.5	0	M5	Ф100	Ф80
71 **	71	112	90	45	Ф14	30	5	11	7x10	1-M20X1.5	Ф85	Ф70	Ф105	2.5	0	M6	Ф115	Φ95
80	80	125	100	50	Ф19	40	6	15.5	10x13	1-M20X1.5	Ф100	Ф80	Ф120	3.0	0	M6	Ф130	Ф110
90S	90	140	100	56	Ф24	50	8	20	10x13	1-M20X1.5	Ф115	Ф95	Ф140	3.0	0	M8	Ф130	Ф110
90L1/L2	90	140	125	56	Ф24	50	8	20	10x13	1-M20X1.5	Ф115	Ф95	Ф140	3.0	0	M8	Ф130	Ф110
100 **	100	160	140	63	Ф28	60	8	24	10x13	1-M20X1.5	Ф130	Ф110	Ф160	3.5	0	M8	Ф165	Ф130
112	112	190	140	70	Ф28	60	8	24	12x16	2-M25X1.5	Ф130	Ф110	Ф160	3.5	0	M8	Ф165	Ф130
132S	132	216	140	89	Ф38	80	10	33	12x16	2-M25X1.5	Ф165	Ф130	Ф200	3.5	0	M10	Ф215	Ф180
132M/L	132	216	178	89	Ф38	80	10	33	12x16	2-M25X1.5	Ф165	Ф130	Ф200	3.5	0	M10	Ф215	Ф180

FRAME		B34B			AC	AD	AA	L	LCC*	LCCL*	LCA*	TBS	TBW	TBH	SS	XX	ZZ	CC	Y
	P	T	R	S			GE EL		10 TE		1917								
56					Ф120	156/151	110	195				14/21	88/73	88/73	МЗ	8	12	2.5	0.5
63	F120	3.0	0	M6	Ф130	173/165	120	215	232	265	283	14/21	94/80	94/80	M4	10	15	3.3	0.8
71 **	F140	3.0	0	M8	Ф145	188/180	132	240(254)	252(267)	307	345	20/27	94/80	94/80	M5	12	18	4.2	0.8
80	F160	3.5	0	M8	Ф165	217	160	290	300	353	390	27	105	105	M6	16	22	5	1
908	F160	3.5	0	M8	Ф185	235	175	310	320	367	448	30	105	105	M8	20	25	6.8	1
90L1/L2	F160	3.5	0	M8	Ф185	235	175	335/365	345/375	392	463	30	105	105	M8	20	25	6.8	1
100 **	F200	3.5	0	M10	Ф205	252	196	368(386)	392(410)	474	445	26	105	105	M10	22	28	8.5	1.5
112	F200	3.5	0	M10	Ф230	292	220	395	410	483	455	32	112	119	M10	22	28	8.5	1.5
1325	F250	4.0	0	M12	Ф270	325	252	436	468	553	636	38	112	119	M12	28	34	10.2	1.5
132M/L	F250	4.0	0	M12	Ф270	325	252	474/500	484/510	564/590	648/674	38	112	119	M12	28	34	10.2	1.5

<sup>\*\* :</sup> This frame size has two housing sizes, the rated output is for normal ( refer to the figures in the bracket " ( ) " )

<sup>&</sup>quot;L" size and increased output is for the bigger "L" sizes



## TAL SERIES

# TAL

## ALUMINIUM HOUSING










TAL series aluminum housing single-phase dual-capacitor asynchronous motors, with latest design in entirety, are made of selected quality materials and conform to the IEC standard.


TAL motors have good performance, safety and reliable operation, nice appearance and, can be maintained very conveniently, while with low noises, lifta vibrator and at the same time of lightweight and simple construction. The compositive performance is good, the multiple of starting torque is 1.8-2.5. These series motors are suitable for the occasion where the requirements of big starting torque and high over load, such as air-compressors, pumps, fans, medical apparatus and 'instruments, and many other small machines














Frame					ħ	IOL	INTIN	G DIM	ENSIONS															VER					FTSC		
Size							IMB14	4:										IMB5					Di	MENS	HONS			DII	MENS	IONS	
	Α	В	С	D	E	F	G	н	K	M	N	P	R	S	Т	M	N	Р	R	S	Ť	AA	AC	AD	HD	L	SS	XX	ZZ	CC	Y
63	100	80	40	11	23	4	8.5	63	7X10	75	60	90	0	M5	2.5	115	95	140	0	Ф10	3.0	120	130	179	116	212	M4	10	15	3.3	0.8
71	112	90	45	14	30	5	11	71	7X10	185	70	105	0	M6	2.5	130	110	160	0	Ф10	3.5	132	145	194	123	255	M5	12	18	4.2	0.8
80	125	100	50	19	40	6	15.5	80	10X13	100	80	120	0	M6	3.0	165	130	200	0	Ф12	3.5	157	165	223	143	290	M6	16	22	5	1
908	140	100	56	24	50	8	20	90	10X13	115	95	140	0	M8	3.0	165	130	200	0	Ф12	3.5	172	185	240	150	335	M8	20	25	6.8	1
90L	140	125	56	24	50	8	20	90	10X13	115	95	140	0	M8	3.0	165	130	200	0	Ф12	3.5	172	185	240	150	365	M8	20	25	6.8	1
100L	160	140	63	28	60	8	24	100	12X15	130	110	160	0	M8	3.5	215	180	250	0	Ф15	4.0	196	205	260	160	445	M10	22	28	8.5	1.5
112M	190	140	70	28	60	8	24	112	12X15	130	110	160	0	M8	3.5	215	180	250	0	Ф15	4.0	222	230	295	183	453	M10	22	28	8.5	1.5

Model	Power (kW)	Current (A)	Speed (r/min)	Eff.	Power Factor	Rated Torque	Tstart/Tn (Times)	TmaxlTn (Times)	Starting Current	Run Capactior	Start Capacitor	Noise dB(A)	W.t. (Kg)
	a Secretar		************	(%)	0.00000	(N M)	Noncomme	Nonzeroza.	(A)	(μ f/V)	(μ f/V)	35(3)	(115)
TAL - 631- 2	0.18	1.31	2750	65	0.92	0.63	2.5	1.7	8	8 μ F/450V	40 μ F/250V	70	4.2
TAL - 632- 2	0.25	1.76	2760	67	0.92	0.87	2.5	1.7	10	10 μ F/450V	50 μ F/250V	73	4.7
TAL - 711- 2	0.37	2.42	2780	70	0.95	1.27	2.5	1.7	15	12 μ F/450V	75 μ F/250V	75	5.3
TAL - 712- 2	0.55	3.45	2790	73	0.95	1.88	2.5	1.7	20	16 μ F/450V	100 μ F/250V	76	7.4
TAL - 801-2	0.75	4.54	2800	74	0.97	2.59	2.5	1.7	30	20 μ F/450V	100 μ F/250V	76	9.5
TAL - 802- 2	1.1	6.45	2810	76	0.97	3.74	2.5	1.7	40	25 μ F/450V	150 μ F/250V	79	11.2
TAL - 90S- 2	1.5	8.62	2810	78	0.97	5.10	2.5	1.8	55	40 μ F/450V	150 μ F/250V	84	14
TAL - 90L- 2	2.2	12.5	2810	79	0.97	7.48	2.2	1.8	75	50 μ F/450V	250 μ F/250V	84	17
TAL - 100L- 2	3.0	16.6	2830	80	0.98	10.12	2.2	2.0	95	60 μ F/450V	400 μ F/300V	88	25
TAL - 112M- 2	3.7	20.5	2850	80	0.98	12.40	2.0	2.0	120	60 μ F/450V	500 μ F/300V	90	30.5
TAL - 631-4	0.12	1.04	1350	55	0.91	0.85	2.5	1.6	6	10 μ F/450V	40 μ F/250V	- 64	4
TAL - 632- 4	0.18	1.54	1360	56	0.91	1.26	2.5	1.6	8.5	12 μ F/450V	40 μ F/250V	64	4.8
TAL - 711- 4	0.25	1.94	1380	61	0.92	1.73	2.5	1.6	10	14 μ F/450V	50 μ F/250V	66	5.9
TAL - 712- 4	0.37	2.80	1380	62.5	0.92	2.56	2.5	1.5	15	16 μ F/450V	75 μ F/250V	68	6.9
TAL - 801- 4	0.55	3.80	1400	67	0.94	3.75	2.5	1.7	20	20 μ F/450V	100 μ F/250V	71	9.6
TAL - 802- 4	0.75	4.75	1410	73	0.94	5.08	2.5	1.7	30	25 μ F/450V	150 μ F/250V	71	10.8
TAL - 90S- 4	1.1	6.76	1410	74.5	0.95	7.45	2.2	1.8	40	30 μ F/450V	150 μ F/250V	74	13.5
TAL - 90L- 4	1.5	9.03	1420	76	0.95	10.09	2.2	1.8	55	40 μ F/450V	200 μ F/250V	79	16.5
TAL - 100L1- 4	2.2	12.6	1430	78	0.97	14.69	2.2	1.8	75	50 μ F/450V	300 μ F/250V	79	24
TAL - 100L2-4	3	17.0	1440	79	0.97	19.90	2.2	1.8	95	60 μ F/450V	400 μ F/250V	83	30
TAL - 112M- 4	3.7	20.7	1440	80	0.97	24.54	2.0	2.0	120	60 μ F/450V	500 μ F/250V	86	36



# TAB ALUMINIUM HOUSING

# ASYNCHONOUS THREE-PHASE BRAKE MOTORS WITH SQUIRREL CAGE ROTOR DIRECT CURRENT BRAKE







TAB series -enclosed construction externally ventilated -sizes 63 - 160

The brake-motors of the **TAB** series result from coupling an asynchronous three-phase motor and an electromagnetic D.C. brake unit. Due to their eliability and operating safety, as well as their quick braking time (connection & disconnection time = 5-80 milliseconds) they are suitable for a great variety of applications. as:

- Braking of loads or tourges on driving shaft.
- Braking of rotating masses to reduce any lost-time.
- Braking operations to increase the set-up precision.
- Braking of machine parts, according to safety rules.

Please refer to the TA motor overall dimensions

## Transm ELEKTRIK MOTOR

## TECHNICAL DATA



#### 2 poles-3000rpm-50Hz

Model	Power (KW)	Speed (r/min)	Eff. N	Power factor	Rat	ed Curren	t (A)	Tstart/Tn (Times)	Tmax/Tn (Times)	Tmin/Tn (Times)	ls/In	Noise dB(A)
					230V	400V	690V					
TAB - 631- 2	0.18	2710	63	0.75	0.95	0.55	0.32	2.2	2.4	1.6	6	61
TAB - 632- 2	0.25	2710	65	0.78	1.23	0.71	0.41	2.2	2.4	1.6	6	61
TAB - 633- 2	0.37	2710	65	0.78	1.82	1.05	0.61	2.2	2.4	1.6	6	62
TAB - 711- 2	0.37	2730	70	0.79	1.67	0.97	0.56	2.2	2.4	1.6	6	64
TAB - 712- 2	0.55	2760	71	0.79	2.45	1.42	0.82	2.2	2.4	1.6	6	64
TAB - 713- 2	0.75	2730	72	0.82	3.18	1.83	1.06	2.2	2.4	1.5	6	65
TAB - 801- 2	0.75	2770	73	0.84	3.06	1.77	1.02	2.2	2.4	1.5	6	67
TAB - 802- 2	1.1	2770	76.2	0.83	4.35	2.51	1.45	2.2	2.4	1.5	6	67
TAB - 803- 2	1.5	2800	78.5	0.83	5.87	3.32	1.92	2.2	2.4	1.5	6	70
TAB - 90S- 2	1.5	2840	78.5	0.84	5.76	3.28	1.90	2.2	2.4	1.5	6	72
TAB - 90L1- 2	2.2	2840	81	0.85	8.0	4.61	2.66	2.2	2.4	1.4	6	72
TAB - 90L2- 2	3	2840	82.6	0.86	10.56	6.10	3.52	2.2	2.4	1.4	6	74
TAB - 100L1- 2	3	2840	82.6	0.87	10.44	6.03	3.48	2.2	2.3	1.4	7	76
TAB - 100L2- 2	4	2850	84.2	0.87	13.65	7.88	4.55	2.2	2.3	1.4	7.5	77
TAB - 112M- 2	4	2880	84.2	0.87	13.65	7.88	4.55	2.2	2.3	1.4	7.5	77
TAB - 112L- 2	5.5	2880	85.7	0.88	18.23	10.53	6.08	2.2	2.3	1.2	7.5	78
TAB - 132S1- 2	5.5	2900	85.7	0.88	18.23	10.53	6.08	2	2.2	1.2	7.5	80
TAB - 132S2- 2	7.5	2920	87	0.88	24.49	14.14	8.16	2	2.2	1.2	7.5	80
TAB - 132M1- 2	9.2	2930	88	0.89	29.87	17.25	9.96	2	2.2	1.2	7.5	81
TAB - 132M2- 2	11	2930	88.4	0.9	34.57	19.96	11.52	2	2.2	1.2	7.5	83
TAB - 160M1- 2	11	2940	88.4	0.9	34.57	19.96	11.52	2	2.2	1.2	7.5	86
TAB - 160M2- 2	15	2940	89.4	0.91	46.09	26.61	15.36	2	2.2	1.2	7.5	86
TAB - 160L- 2	18.5	2940	90	0.91	56.47	32.6	18.82	2	2.2	1.1	7.5	86

Туре	Brake Type k	Brake torque Nm	Brake Rated Power W	J brake Pd <sup>2</sup> kgm <sup>2</sup>	No.of Starts/Hr. Under no load	Delayed Cut-in Time * Msec.	Quick Cut-in Time Msec.	Cut out Time Msec.	Noise dB(A)
TAB 63	K1	5	15	0.00005	3000	45	20	10	62
TAB 71	K2	12	20	0.00014	3000	50	30	15	64
TAB 80	КЗ	16	25	0.00021	1300	55	30	15	67
TAB 90S	K4	20	30	0.00039	1100	65	40	15	72
TAB 90S	K4 D	40	30	0.00078	1100	65	40	15	72
TAB 90L	K4	20	30	0.00039	1100	65	40	15	72
TAB 90L	K4 D	40	30	0.00078	1100	65	40	15	72
TAB 100L	K5	40	45	0.00104	900	75	45	20	76
TAB 100L	K6	60	50	0.00135	900	180	85	25	76
TAB 112 MT	K5	40	45	0.00104	880	75	45	20	77
TAB 112M	K6	60	50	0.00135	880	180	85	25	78
TAB 132S	K7	90	55	0.00219	480	200	95	50	80
TAB 132S	K7 D	180	55	0.00438	480	200	95	50	80
TAB 132M	K7	90	55	0.00219	450	200	95	50	80
TAB 132M	K7 D	180	55	0.00438	480	200	95	50	80
TAB 160MT	K7 D	180	55	0.00438	350	200	95	50	86
TAB 160L	K8	200	60	0.00408	350	210	100	60	86
TAB 160L	K8 D	400	60	0.00816	350	210	100	60	86

- Motor with increased braking torque on request
- ★ On request, delayed brake cut in time for lifting equipments, We suggest double disk brake D for lifting equipments.







#### ECHNICAL FEATURES

#### 4 poles - 1500 rpm- 50Hz

Model	Power (KW)	Speed (r/min)	Eff. (%)	Power factor	Rat	ed Currei	nt (A)	Tstar tan (Times)	Tmaxa n (Times)	Tmin/Tn (Times)	ls/In	Noise dB(A)
					230V	400V	690V		-, 1 - 1 1			
TAB - 631- 4	0.12	1350	57	0.64	0.82	0.47	0.27	2.2	2.4	1.7	6	52
TAB - 632- 4	0.18	1350	59	0.65	1.17	0.68	0.39	2.2	2.4	1.7	6	52
TAB - 633- 4	0.25	1350	60	0.66	1.58	0.91	0.53	2.2	2.4	1.7	6	54
TAB - 711- 4	0.25	1350	60	0.72	1.45	0.84	0.48	2.2	2.4	1.7	6	55
TAB - 712- 4	0.37	1370	65	0.74	1.92	1.11	0.64	2.2	2.4	1.7	6	55
TAB - 713- 4	0.55	1380	66	0.75	2.78	1.60	0.93	2.2	2.4	1.7	6	57
TAB - 801- 4	0.55	1370	67	0.75	2.74	1.58	0.91	2.2	2.4	1.7	6	58
TAB - 802- 4	0.75	1380	72	0.78	3.34	1.93	1.11	2.2	2.4	1.6	6	58
TAB - 803- 4	1.1	1390	76.2	0.78	4.63	2.67	1.54	2.2	2.4	1.6	6	60
TAB - 90S- 4	1.1	1400	76.2	0.79	4.57	2.64	1.52	2.2	2.4	1.6	6	61
TAB - 90L- 4	1.5	1400	78.5	0.8	5.97	3.45	1.99	2.2	2.4	1.6	6	61
TAB - 90L2- 4	2.2	1400	81	0.8	8.45	4.90	2.83	2.2	2.4	1.5	7	63
TAB - 100L1- 4	2.2	1420	81	0.81	8.38	4.84	2.79	2.2	2.3	1.5	7	64
TAB - 100L2- 4	3	1420	82.6	0.81	11.21	6.47	3.74	2.2	2.3	1.5	7	64
TAB - 100L3- 4	4	1430	84.2	0.82	14.18	8.36	4.83	2.2	2.3	1.5	7	65
TAB - 112M- 4	4	1430	84.2	0.83	14.31	8.26	4.77	2.2	2.2	1.5	7	65
TAB - 112L- 4	5.5	1440	85.7	0.83	19.33	11.16	6.44	2.2	2.2	1.4	7	68
TAB - 132S- 4	5.5	1450	85.7	0.84	19.1	11.03	6.37	2.2	2.2	1.4	7	71
TAB - 132M- 4	7.5	1450	87	0.85	25.35	14.64	8.45	2.2	2.2	1.4	7	71
TAB - 132L1- 4	9.2	1460	87.5	0.85	30.92	17.85	10.31	2.2	2.2	1.4	7.5	74
TAB - 132L2- 4	10	1460	88	0.85	33.42	19.3	11.14	2.2	2.2	1.4	7.5	74
TAB - 132L3- 4	11	1460	88.4	0.86	36.17	20.88	12.06	2.2	2.2	1.4	7.5	74
TAB - 160M- 4	11	1460	88.4	0.87	35.76	20.64	11.92	2.2	2.2	1.4	7	75
TAB - 160L- 4	15	1460	88.4	0.87	48.76	28.15	16.25	2.2	2.2	1.4	7.5	75

	Туре	Brake Type k	Brake torque N m	Brake Rated Power W	J brake Pd <sup>2</sup> kgm <sup>2</sup>	No.of Starts/Hr. Under no load	Delayed Cut-in Time* Msec.	Quick Cut-in Time Msec.	Cut out Time Msec.	Noise dB(A)
	TAB 63	K1	5	15	0.00005	3000	45	20	10	52
	TAB 71	K2	12	20	0.00014	3000	50	30	15	55
	TAB 80	K3	16	25	0.00021	1300	55	30	15	58
	TAB 90S	K4	20	30	0.00039	1100	65	40	15	61
9	TAB 90S	K4 D	40	30	0.00078	1100	65	40	15	61
	TAB 90L	K4	20	30	0.00039	1100	65	40	15	63
Þ	TAB 90L	K4 D	40	30	0.00078	1100	65	40	15	63
	TAB 100L	K5	40	45	0.00104	900	75	45	20	64
	TAB 100L	K6	60	50	0.00135	900	180	85	25	65
	TAB 112MT	K5	40	45	0.00104	880	75	45	20	65
	TAB 112 M	K6	60	50	0.00135	880	180	85	25	65
	TAB 132S	K7	90	55	0.00219	480	200	95	50	71
•	TAB 132S	K7 D	180	55	0.00438	480	200	95	50	71
	TAB 132M	K7	90	55	0.00219	450	200	95	50	71
0	TAB 132M	K7 D	180	55	0.00438	480	200	95	50	71
	TAB 160MT	K7 D	180	55	0.00438	350	200	95	50	75
	TAB 160L	K8	200	60	0.00408	350	210	100	60	75
	TAB 160L	K8 D	400	60	0.00816	350	210	100	60	75

- Motor with increased braking torque on request
- ★ On request, delayed brake cut in time for lifting equipments, We suggest double disk brake D for lifting equipments.

## Transm ELEKTRIK MOTOR

## TECHNICAL DATA



6 poles - 1000 rpm- 50Hz

Model	Power (KW)	Speed (r/min)	Eff. (%)	Power factor	Rat	ed Currer	nt (A)	Tstar tan (Times)	Tmaxan (Times)	Tminan (Times)	is/in	Noise dB(A)
	V				230V	400V	690V					
TAB - 631- 6	0.09	840	42	0.61	0.88	0.51	0.29	2	2	1.5	3.5	50
TAB - 632- 6	0.12	850	45	0.62	1.08	0.62	0.36	2	2	1.5	3.5	50
TAB - 711- 6	0.18	880	56	0.66	1.22	0.70	0.41	1.6	1.7	1.5	4	52
TAB - 712- 6	0.25	900	59	0.7	1.51	0.87	0.50	2.1	2.2	1.5	4	52
TAB - 713- 6	0.37	890	61	0.69	2.2	1.27	0.73	2	2.1	1.5	4	54
TAB - 801- 6	0.37	900	62	0.7	2.13	1.23	0.71	1.9	1.9	1.5	4	56
TAB - 802- 6	0.55	900	67	0.72	2.85	1.65	0.95	2	2.3	1.5	4	56
TAB - 803- 6	0.75	900	68	0.72	3.83	2.21	1.28	2	2.3	1.5	4	58
TAB - 905- 6	0.75	920	69	0.72	3.77	2.18	1.26	2.2	2.2	1.5	5.5	59
TAB - 90L- 6	1.1	925	72	0.73	5.23	3.02	1.74	2.2	2.2	1.3	5.5	59
TAB - 100L- 6	1.5	945	74	0.76	6.67	3.85	2.22	2.2	2.2	1.3	6	61
TAB - 112M- 6	2.2	955	78	0.76	9.28	5.36	3.09	2.2	2.2	1.3	6	64
TAB - 132S- 6	3	960	79	0.76	12.49	7.21	4.16	2	2	1.3	6.5	64
TAB - 132M1- 6	4	960	80.5	0.76	16.35	9.44	5.45	2	2	1.3	6.5	68
TAB - 132M2- 6	5.5	960	83	0.77	21.51	12.42	7.17	2	2	1.3	6.5	68
TAB - 132L- 6	7.5	960	85	0.77	28.65	16.54	9.55	2	2	1.3	6.5	68
TAB - 160M- 6	7.5	960	86	0.8	27.25	15.73	9.08	2	2.2	1.3	6.5	68
TAB - 160L- 6	11	960	87.5	0.79	39.78	22.97	13.26	2	2.2	1.2	6.5	73

Туре	Brake Type k	Brake torque N	Brake Rated Power	J brake Pd <sup>2</sup>	No.of Starts/Hr. Under no	Delayed Cut-in Time *	Quick Cut-in Time	Cut out Time	Noise dB(A)
		Nm	W	kgm <sup>2</sup>	load	Msec.	Msec.	Msec.	
TAB 63	K1	5	15	0.00005	3000	45	20	10	50
TAB 71	K2	12	20	0.00014	3000	50	30	15	52
TAB 80	K3	16	25	0.00021	1300	55	30	15	56
TAB 905	K4	20	30	0.00039	1100	65	40	15	59
● TAB 905	K4 D	40	30	0.00078	1100	65	40	15	59
TAB 90 L	K4	20	30	0.00039	1100	65	40	15	59
● TAB 90 L	K4 D	40	30	0.00078	1100	65	40	15	59
TAB 100 L	K5	40	45	0.00104	900	75	45	20	61
● TAB 100 L	K6	60	50	0.00135	900	180	85	25	61
TAB 112MT	K5	40	45	0.00104	880	75	45	20	64
TAB112M	K6	60	50	0.00135	880	180	85	25	64
TAB 132 S	K7	90	55	0.00219	480	200	95	50	64
TAB 132 S	K7 D	180	55	0.00438	480	200	95	50	64
TAB 132 M	K7	90	55	0.00219	450	200	95	50	68
● TAB 132 M	K7 D	180	55	0.00438	480	200	95	50	68
TAB 160 MT	K7 D	180	55	0.00438	350	200	95	50	68
TAB 160 L	K8	200	60	0.00408	350	210	100	60	73
TAB 160 L	K8 D	400	60	0.00816	350	210	100	60	73

- Motor with increased braking torque on request
- ★ On request, delayed brake cut in time for lifting equipments, We suggest double disk brake D for lifting equipments.







8 poles - 750 rpm- 50Hz

Model	Power (KW)	Speed (r/min)	Eff.	Power factor	Rat	ed Currer	it (A)	Tstart/Tn (Times)	TmaxiTn (Times)	Tmina n (Times)	3 2.7 2.8 2.7 2.8 3	Noise dB(A)
					230V	400V	690V					
TAB - 711-8	0.09	680	48	0.56	0.84	0.48	0.28	1.5	1.7	1.3	3	50
TAB - 712- 8	0.12	690	51	0.59	1.00	0.58	0.33	1.6	1.7	1.3	2.7	50
TAB - 801- 8	0.18	680	51	0.61	1.45	0.84	0.48	1.5	1.7	1.3	2.8	52
TAB - 802- 8	0.25	680	56	0.61	1.83	1.06	0.61	1.6	2	1.3	2.7	52
TAB - 905- 8	0.37	680	63	0.63	2.33	1.35	0.78	1.6	1.8	1.3	2.8	56
TAB - 90L- 8	0.55	680	66	0.65	3.21	1.85	1.07	1.6	1.8	1.3	3	56
TAB - 100L1- 8	0.75	710	66	0.67	4.24	2.45	1.41	1.7	2.1	1.3	3.5	59
TAB - 100L2- 8	1.1	710	72	0.69	5.54	3.20	1.85	1.7	2.1	1.2	3.5	59
TAB - 112M- 8	1.5	710	74	0.68	7.45	4.30	2.48	1.8	2.1	1.2	4.2	61
TAB - 1325- 8	2.2	720	75	0.71	10.33	5.96	3.44	2	2	1.2	5.5	64
TAB - 132M- 8	3	720	77	0.73	13.34	7.70	4.45	2	2	1.2	5.5	64
TAB - 160M1-8	4	730	80	0.73	17.12	9.89	5.71	1.9	2.1	1.2	6	68
TAB - 160M2- 8	5.5	720	83.5	0.74	22.25	12.85	7.42	2	2.2	1.2	6	68
TAB - 160L- 8	7.5	720	85	0.75	29.41	17.0	9.8	1.9	2.2	1.2	6	68

	Туре	Brake Type k	Brake torque N m	Brake Rated Power W	J brake Pd <sup>2</sup> kgm <sup>2</sup>	No.of Starts/Hr. Under no load	Delayed Cut-in Time*	Quick Cut-in Time Msec.	Cut out Time Msec.	Noise dB(A)
	TAB 63	K1	5	15	0.00005	3000	45	20	10	50
V.	TAB 71	K2	12	20	0.00014	3000	50	30	15	50
	TAB 80	КЗ	16	25	0.00021	1300	55	30	15	52
	TAB 90 S	K4	20	30	0.00039	1100	65	40	15	56
	TAB 90 S	K4 D	40	30	0.00078	1100	65	40	15	56
	TAB 90 L	K4	20	30	0.00039	1100	65	40	15	56
	TAB 90 L	K4 D	40	30	0.00078	1100	65	40	15	56
	TAB 100 L	K5	40	45	0.00104	900	75	45	20	59
	TAB 100 L	K6	60	50	0.00135	900	180	*85	25	59
	TAB 112 MT	K5	40	45	0.00104	880	75	45	20	61
Т	TAB 112 M	K6	60	50	0.00135	880	180	85	25	61
	TAB 132 S	K7	90	55	0.00219	480	200	95	50	64
0	TAB 132 S	K7 D	180	55	0.00438	480	200	95	50	64
	TAB 132 M	K7	90	55	0.00219	450	200	95	50	64
	TAB 132 M	K7 D	180	55	0.00438	480	200	95	50	64
	TAB 160 MT	K7 D	180	55	0.00438	350	200	95	50	68
	TAB 160 L	K8	200	60	0.00408	350	210	100	60	68
0	TAB 160 L	K8 D	400	60	0.00816	350	210	100	60	68

Motor with increased braking torque on request

<sup>★</sup> On request, delayed brake cut in time for lifting equipments, We suggest double disk brake D for lifting equipments.

## Transm ELEKTRIK MOTOR

## **OPERATING**



#### **OPERATING PRINCIPLE**

The direct current brake is fed by means of an electronic circuit with diode bridge (rectifier) situated inside the terminal-box.

- (5) When feeding the electromagnet
- (4) The movable anchor is attracted towards the same,
- (9) thus loading the braking torque springs,
- (2) And allowing the disk
- (6) Equipped with friction packing and fitted on the groove hub
- (1) To turn solitary the motor shaft,
- (7) By means of a key
- (4) By interrupting the feeding, the movable anchor
- (9) Pushed by the braking torque springs
- (2) Exerts a pressure upon the friction surface of the disk

Thus causing its stopping.

#### ADJUSTMENT OF THE AIR GAP.


- (11) The air gap
- (5) Is the distance between the electromagnet
- (9) And the movable anchor
- (2) The air gap has to be regularly checked, since due to the wear of the friction packing It tends to increase.
- (3) Act no the brake adjusters
- (8) After having unloosen the screws To bring the air gap to the required value.
- (10) Act on the ring nut
- (9) which acts on the braking torque springs to adjust the braking torque.


Pls. contact our technical department for information on the air gap adjustn


#### HANDRELEASE WITH LEVER


Upon request a hand release with lever can be supplied.

- (12) In case of a current cutoff, acting on the lever
- (4) The release, connected to the movable anchor
- (2) overcomes the springs pressure, thus detaching the movable anchor from the disc friction packing allowing the shaft to turn.











ASYNCHRONOUS THREE-PHASE BRAKE MOTORS with direct current 63-160 Type C FECCL Frame B3 Sizes 63-160, Type FC FECCLFrame B5 Sizes 63-160 Enclosed construction -External ventilation





#### SPARE PARTS

- 1. Front bearing
- 2. Front shield
- 3. Winding
- 4. Frame with stator package
- 5. Shaft with rotor
- 6. Rear bearing
- 7. Spring
- 8. Rear shield
- 9. Adjusting bush
- 10. Brake disc
- 11. Moving anchor
- 12. Electromagnet coil with diode
- 13. Fixing screws for brake
- 14. Cooling fan
- 15. Fan hood
- 16. Ring nut
- 17. Spring
- 18. See gearing
- 19. Key brake side
- 20. Toothed pinion
- 21. Fixing screw for fan hood
- 22. Fixing crew for terminal-box
- 23. Terminal-box
- 24. able-holder
- 25. Packing
- 26. Terminal-block
- 27. Tie-bolt
- 28. Coupling side key
- 29. Fixing screw for shield
- 30. Flange shield

## **HELICAL BEVEL GEAR**





# NEW PRODUCT



TKM SERIES
INTERCHANGEABLE
MOTOVARIO SERIES

TKB SERIES
INTERCHANGEABLE
BONFIGLIOLI SERIES

Туре	Stage	Ratio	Motor size up to	Motor power up to	Torque MAX (Nm)	Worm gear units type
TKM 27B	2	7.73 ~ 58.36	90	1.5	140	YMRV050
TKM 27C	3	52.36 ~ 291.79	90	1.5	140	YMRV050
TKM 37B	2	7.60 ~ 60.50	90	1.5	200	YMRV063
TKM 37C	3	52.48 ~ 302.52	90	1.5	200	YMRV063
TKM 47B	2	7.48 ~ 59.71	100 - 112	4	400	YMRV075
TKM 47C	3	49.18 ~ 298.57	100 - 112	4	400	YMRV075
TKM 57B	2	7.48 ~ 59.04	100 - 112	5.5	600	YMRV090
TKM 57C	3	49.18 ~ 295.18	100 - 112	5.5	600	YMRV090
TKB 37B	2	7.60 ~ 60.50	90	1.5	200	W63
TKB 37C	3	52.48 ~ 302.52	90	1.5	200	W63
TKB 47B	2	7.48 ~ 59.71	100 - 112	4	400	W75
TKB 47C	3	49.18 ~ 298.57	100 - 112	4	400	W75
TKB 57B	2	7.48 ~ 59.04	100 - 112	5.5	600	W86
TKB 57C	3	49.18 ~ 295.18	100 - 112	5.5	600	W86

#### DESIGN FEATURES :

- 1. DRIVEN BY BEVEL GEAR, HAS BIG RATIO.
- 2. HIGH EFFICIENCY, ENERGY SAVING AND ENVIRONMENTAL PROTECTION
- 3. ALUMINIUM CASTING, LIGHT IN WEIGHT
- 4. THE MOUNTING OF TKM SERIES ARE COMPATIBLE WITH MOTOVARIO SERIES
- 5. THE MOUNTING OF TKB SERIES ARE COMPATIBLE WITH BONFIGLIOLI SERIES
- 6. MODULAR AND MULTISTRUCTURE CAN MEET THE DEMAND OF VARIOUS CONDITIONS

Туре	Ratio	Input speed(n1)	Efficiency(η)
TKM37B	59.71	1400	94%
YMRV063	60	1400	62%
W63	64	1400	67%

## Transm SPEED REDUCER

## **HELICAL GEAR**

## ELICAL GEAR REDUCER

#### SUMMARIZE

TR Series helical gearmotor is a new generation mechanic-electrical integrated product, which designed basing on the modular system. It can be connected respectively with motors such as normal motor, brake motor, explosion-proof motor, frequency conversion motor, servo motor, IEC motor and so on. It can be mounted discretionary six orientation in solid space. This kind of product is widely used in drive fields such as textile, foodstuff, beverage, chemical industry, automatic arm ladder, automatic storage equipment, metallurgy, tobacco, environment-protection, logistics and so on.

#### PERFORMANCE CHARACTERISTICS

- 1. Transmission ratio with fine stage covers a wide range;
- 2. Compact structure takes up small room;
- 3. low vibration; low noise; low energy dissipation;
- 4. Refined design; reliable and wearable; wide usage;
- 5. Modular, multistructure, can be combined in many forms to meet needs of all kinds of transmission conditions.

TR Series helical gearmotor of 1-stage, 2-stage or 3-stage helical gears unit and motor. The helical gear which use the material of high quality alloy steel with the surface hardened takes shape through processing of high-precision equipment. Except the TR..27 housing with aluminum alloy, all are cast iron housing. housing is exactly processed to ensure the shape and position precision. And it reaches advantageous performance such as: strong bearing capacity, long service-life; small volume; big ratio; light weight, high efficiency, low noise.

TR Series helical gearmotor has more than ten models. Combined with TRF series, the multi-stage gear reduction can be achieved. Power 0.12-160KW; Ratio 1.3-27001;Torque 69-18000Nm. It can connect (foot, flange) discretionary and use multi-mounting positions according to customers' requirements.








## SPEED REDUCER









#### 1. 1 Products characteristics

- Modularity;
- High efficiency;
- Low noise;
- Space effective, refined design;
- Universal mounting;
- Aluminium housing, light in weight;
- Gears in carbonize hard, durable;
- Multistructure, can be combined in many forms to meet needs of all kinds of transmission conditions.



CHC..P(IEC)
Foot-mounted helical gear



CHC..HS Shaft input foot - mounted helical gear unit



CHCF..P(IEC)
Flange-mounted helical gear unit



CHCF..HS Shaft input Flangemounted helical gear unit



CHCZ..P(IEC)
B14 Flange-mounted helical gear unit



CHCZ..HS Shaft input B14 Flangemounted helical gear unit

CHC Series helical gear units has more than 4 types. Power  $0.12 \sim 4 \text{KW}$ ; Ratio 3.66-54; Torque max 120-500 Nm. It can be connected (foot, flange) discretionary and use multi-mounting positions according to customers requirements.



## SPEED REDUCER





## Products characteristics

YMRV series worm gear units is a new-generation of product developed by our company on the basis of perfecting WJ series products with a compromise of advanced technology both at home and abroad, its main features are as follows:

- Made of high-quality aluminum alloy, light in weight and nonrusting.
- 2. Large in output torque.
- Smooth in running and low in noise, can work long time in dreadful conditions.
- 4. High in radiating efficiency.
- Good-looking in appearance, durable in service life and small in volume.
- 6. Suitable for omnibearing installation.

### Surface painting

Aluminum alloy housing:

- Shot blasting and special antiseptic treatment on the aluminum alloy surface.
- After phosphating, paint with RAL 5010 blue . Cast iron housing :
  - First paint with red antirust paint, then paint with RAL 5010 blue

#### Main materials

- 1. Housing: die-cast aluminum alloy (frame size: 025 to 105); cast iron (frame size: 110 to 130).
- Worm: 20Cr, carbonize & quencher heat treatment make the hardness of gear's surface up to 56~62 HRC retain carburization layer's thickness between 0.3 and 0.5mm after precise grinding.
- 3. Worm wheel: wearable stannum bronze alloy.













## MINI HELICAL GEAR







#### PAINT

- Shot blasting and special antiseptic treatment on the aluminum alloy surface
- After phosphating , Paint with silvery white paint

#### GENERAL INTRODUCTION

- Made of high quality die casting aluminum alloy housing, good-looking in appearance, suitable for universal mounting.
- Helical gear made of high-strength alloy make construction more compacter, and housing smaller, efficiency higher, output torque bigger.
- Hardened gears with fine grinded has little metamorphosis and high precision, low noise and stably running, also can work long time in dreadful conditions.
- The diameter of output shaft have 4 specifications, such as Φ18, Φ22, Φ28, Φ32.
- 2nd or 3rd stage transmission, Larger speed ratio range, each single frame size has 14 ratios from 5:1 to 200:1
- Using "NSK" bearing can prolong running life.
- Temperature resistant oil seal can prevent lubricant grease from leaking back to the inner of motor
- Three phase motor combined totally enclosed aluminum motor with aluminum terminal box, can resist water, easily volatilizing heat, run with high efficiency.
- Modularization combination extend the ratio of speed reducer from i = 5:1 to 1400:1

## **OUTPUT TORQUE OF IEC INPUT REDUCER**

Normal ratio			5	10	15	20	25	30	40	50	60	80	100	100	120	160	200
0.12kW	output shaft		Ø18										Ø22				
	M2	50Hz	3.9	7.8	11.7	15.4	19.3	23.5	30.9	37.3	45.0	59.4	75.5	<del>    </del>	91.3	120.9	150.4
	(Nm)	60Hz	3.2	6.5	9.8	12.9	16.1	20.4	25.7	31.1	37.5	49.5	62.9		76.1	100.7	125.4
0.18kW	output shaft		Ø18				Ø22					Ø28					
	M2	50Hz	5.9	11.4	17.2	23.6	29.3	35	45.3	56.7	68.1	90.7	93.5	112.8	135	180.3	225.6
	(Nm)	60Hz	4.9	9.5	14.9	19.7	24.4	29.2	37.8	47.3	56.7	75.6	77,9	94	112.5	150.3	188
0.37kW	output shaft		Ø22				Ø28					Ø32					
	M2	50Hz	11.9	23.1	35.7	47.6	60.5	72.3	93.2	116	138.8	185.3	191.3	231.9	278.5	370.7	427.2
	(Nm)	60Hz	9.9	19.2	29.7	39.6	50.4	60.3	77.6	96.6	115.6	154.4	159.4	193.3	232.1	308.9	356
0.75kW	output shaft		Ø28				Ø32						Ø40				
	M2	50Hz	24.6	48.2	72.9	97.5	122.1	145.7	187.5	235.7	282.9	376.1	387.9	439	527	703	764
	(Nm)	60Hz	20.5	40.2	60.7	81.3	201.8	121.4	156.3	196.4	235.7	313.4	323.2	366	439	585	732
1.5kW	output shaft		Ø32				Ø40						Ø50				
	M2	50Hz	48.2	97.5	145.7	193.9	242.1	272	351	439	527	703	724	878	1060	1230	1230
	(Nm)	60Hz	40.2	81.3	121.4	161.6	201.8	226	293	366	439	585	603	732	878	1170	1230
2.2kW	output shaft		Ø40				Ø50										
	M2	50Hz	67	133	200	266	332	399	515	644	773	1029	1230				
	(Nm)	60Hz	56	111	167	221	277	332	429	537	644	858	1080				

# 以心相交迹



以心相交 成其久以称相交 權失則以利相交 帮去則則

速棄傾散





Type B Series





HMI (DOP Series)



A Section Associated and the section of the section

Type M Series



Type S Series